

LMR BATTERY SPECIFICATIONS	PART NUMBER
	BPU8299

COMPATIBLE RADIOS	Motorola XTS3000, XTS3500, XTS5000, EF Johnson 5100 series
REPLACES OEM BATTERY	NNTN6034A
COMPATIBLE CHARGERS	Endura EC1-MT12, EC1-MT13B, EC1M-MT12, EC1M-MT13B, EC2M-MT13-D, EVC-MT13, EVC-MT13-4 / Motorola NTN1667A / Micro USB compatible
USB CHARGING	Internal circuitry allows charging with 24" USB cable included / status LED indicates charging, charge complete, or fault
VOLTAGE	7.4V
CAPACITY / ENERGY	3000 mAh / 22.2 Wh
CHEMISTRY / CELL TYPE	Li-Ion / Panasonic or equivalent
OPERATING TEMPERATURE	-20° C to +60° C (discharge) / 0° C to +40° C (charge)
CHARGE CYCLES	>300
CHARGE TYPE	Rapid
CONDITIONER COMPATIBLE	Yes (not required for battery run time or cycle life)
PROTECTION TYPES	Short circuit / over-charge / over-discharge / over-temperature monitoring via external charge contact
HOUSING MATERIAL	ABS
HOUSING SEAL	Ultrasonic weld
METAL WELDING	Pure nickel tabs w/ spot welder
CLIP	CL9008
WARRANTY	12 months
PRODUCT PHOTO	