


| | |
|-----------------------------------|------------------|
| LMR BATTERY SPECIFICATIONS | PART NUMBER |
| | BPBA100LI |

| | |
|------------------------|--|
| COMPATIBLE RADIOS | Tait TP8100, TP8110, TP8115, TP8120, TP8135, TP8140 |
| REPLACES OEM BATTERY | TPK-BA-100 |
| COMPATIBLE CHARGERS | Endura TWC1-TA2 (desktop), TWC6M-TA2 (six-unit), TWC1M-TA2 and LEVC-TA2 (in-vehicle) |
| VOLTAGE | 7.2V |
| CAPACITY | 1900 mAh / 13.7 Wh |
| CHEMISTRY | Li-Ion |
| CELL TYPE | Sanyo, Panasonic, or equivalent |
| OPERATING TEMPERATURE | -20° C to +60° C (discharge) / 0° C to +40° C (charge) |
| CHARGE CYCLES | 300 |
| CHARGE TYPE | Rapid |
| CONDITIONER COMPATIBLE | Yes |
| THERMAL PROTECTION | Yes |
| HOUSING MATERIAL | ABS |
| HOUSING SEAL | Ultrasonic weld |
| METAL WELDING | Pure nickel tabs w/ spot welder |
| CLIP | Included |
| WARRANTY | 12 months |
| PRODUCT PHOTO |  |