



<b>LMR BATTERY SPECIFICATIONS</b>	PART NUMBER
	<b>BP5615MH</b>

COMPATIBLE RADIOS	Kenwood TK-260, TK-260G TK-270, TK-272G, TK-360, TK-360G, TK-370, TK-370G, TK-372G, TK-373G, TK-2100, TK-3100, TK-3101, Maxon / Legacy PL2215, PL2245, PL2415, PL2445, Midland PL5161, PL5164
REPLACES OEM BATTERY	KNB-20N
COMPATIBLE CHARGERS	Endura EC1-KW1A, EC1M-KW1A, EC6M-KW1A / Kenwood KSC-15, KSC-16
VOLTAGE	7.2V
CAPACITY	2000 mAh
CHEMISTRY	NiMH
CELL TYPE	FDK, Panasonic, or equivalent
OPERATING TEMPERATURE	-10° C to +65° C (discharge) / 0° C to +40° C (charge)
CHARGE CYCLES	500
CHARGE TYPE	Rapid or trickle
CONDITIONER COMPATIBLE	Yes
PROTECTION TYPES	Short circuit, over-discharge, over-temperature monitoring via charge contact
HOUSING MATERIAL	ABS
HOUSING SEAL	Ultrasonic weld
METAL WELDING	Pure nickel tabs w/ spot welder
CLIP	N/A
WARRANTY	12 months
PRODUCT PHOTO	