

LMR BATTERY SPECIFICATIONS	PART NUMBER
	BP36295LI

COMPATIBLE RADIOS	Vertex Standard VX350, VX351, VX354
REPLACES OEM BATTERY	FNB-V95LI, FNB-V96LI, AAF21X021
COMPATIBLE CHARGERS	Endura EC1-V2-VX4A, EC1M-V2-VX4A, EC6M-V2-VX4A / Vertex Standard VAC-300, VAC-6300
VOLTAGE	7.4V
CAPACITY	2200 mAh / 16.3 Wh
CHEMISTRY	Li-Ion
CELL TYPE	Panasonic or equivalent
OPERATING TEMPERATURE	-20° C to +60° C (discharge) / 0° C to +40° C (charge)
CHARGE CYCLES	300
CHARGE TYPE	Rapid
CONDITIONER COMPATIBLE	Yes (not required for battery performance or cycle life)
PROTECTION TYPES	Short circuit / over-charge / over-discharge / over-temperature monitoring via charge contact
HOUSING MATERIAL	ABS
HOUSING SEAL	Ultrasonic weld
METAL WELDING	Pure nickel tabs w/ spot welding
CLIP	N/A
WARRANTY	12 months
PRODUCT PHOTO	