

<b>LMR BATTERY SPECIFICATIONS</b>	PART NUMBER
	<b>BP8299MHUC</b>

COMPATIBLE RADIOS	Motorola XTS3000, XTS3500, XTS5000
REPLACES OEM BATTERY	RNN4006B (3500 mAh)
COMPATIBLE CHARGERS	Endura EC1-MT13B, EC1M-MT13B, EC2M-MT13-D, EC6M-MT13B, EC12M-MT13-D, EVC-MT13, EVC-MT13-4 / Motorola NTN1667A
VOLTAGE	7.5V
CAPACITY	3800 mAh typical (3700 mAh minimum)
CHEMISTRY	NIMH
CELL TYPE	FDK
CHARGE CYCLES	500
CHARGE TYPE	Rapid or trickle
OPERATING TEMPERATURE	0° C - 50° C (discharge) / 0° C - 40° C (charge)
CONDITIONER COMPATIBLE	Yes
PROTECTION TYPES	Short circuit (with PTC) / over-charge (with NTC)
HOUSING MATERIAL	ABS
HOUSING SEAL	Ultrasonic weld
METAL WELDING	Pure nickel tabs w/ spot welder
CLIP	Included (CL8299)
WARRANTY	12 months
PRODUCT PHOTO	 <div style="border: 1px dashed black; padding: 5px; margin-left: 20px;"> <p><b>Dimensions (LxWxD)</b>          6.17" x 2.33" x 0.88"          156.7 x 59.3 x 22.4 mm</p> <p><b>Weight</b>          0.83 lbs. / 276 g</p> </div>