

LMR BATTERY SPECIFICATIONS	PART NUMBER
	BPKNB48L

COMPATIBLE RADIOS	Kenwood NEXEDGE NX200, NX200G, NX200S, NX205G, NX300, NX300G, NX300S, NX305G, TK5220, TK5320
REPLACES OEM BATTERY	KNB-48L
COMPATIBLE CHARGERS	Endura EC1-KW4A, EC1M-KW4A, EC2M-KW4A-D, EC6M-KW4A, EC12M-KW4A-D, EVC-KW4 / Kenwood KSC-32
VOLTAGE	7.4V
CAPACITY	2500 mAh / 18.5 Wh
CHEMISTRY	Li-Ion
CELL TYPE	Panasonic UR18650ZY
OPERATING TEMPERATURE	-20° C to +60° C (discharge) / 0° C to +45° C (charge)
CHARGE CYCLES	450
CHARGE TYPE	Rapid
CONDITIONER COMPATIBLE	Yes (not required for battery run time or cycle life)
PROTECTION TYPES	Short circuit / over-charge / over-discharge / over-temperature monitoring via charge contact
HOUSING MATERIAL	ABS
HOUSING SEAL	Ultrasonic weld
METAL WELDING	Pure nickel tabs w/ spot welder
CLIP	N/A
WARRANTY	12 months
PRODUCT PHOTO	 <div style="border: 1px dashed black; padding: 10px; margin-left: auto; margin-right: auto;"> <p>Dimensions (H x W x D): 4.12" x 2.29" x .92" (104.8 x 58.2 x 23.4 mm)</p> <p>Weight: 4.83 oz. / 136.8 g.</p> </div>