

| | |
|-----------------------------------|-----------------|
| LMR BATTERY SPECIFICATIONS | PART NUMBER |
| | BPUKNB48 |

| | |
|------------------------|---|
| COMPATIBLE RADIOS | Kenwood NX200, NEXEDGE NX200, NX200G, NX200S, NX205G, NX300, NX300G, NX300S, NX305G, TK5220, TK5320 |
| REPLACES OEM BATTERY | KNB-48L |
| COMPATIBLE CHARGERS | Endura EC1-KW4A, EC-KSC32, EC2M-KW4A-D, EC2M-KW4B-D, EC2M-KW4C-D, EVC-KW4, EC12M-KW4B-D, EC12M-KW4C-D / Kenwood KSC-32 / Micro USB compatible |
| USB CHARGING | Internal circuitry allows charging with 24" USB cable included / status LED indicates charging, charge complete, or fault |
| VOLTAGE | 7.4V |
| CAPACITY / ENERGY | 2500 mAh / 18.5 Wh |
| CHEMISTRY / CELL TYPE | Li-Ion / Panasonic or equivalent |
| OPERATING TEMPERATURE | -20° C to +60° C (discharge) / 0° C to +40° C (charge) |
| CHARGE CYCLES | >300 |
| CHARGE TYPE | Rapid |
| CONDITIONER COMPATIBLE | Yes (not required for battery run time or cycle life) |
| PROTECTION TYPES | Short circuit / over-charge / over-discharge / over-temperature monitoring via external charge contact |
| HOUSING MATERIAL | ABS |
| HOUSING SEAL | Ultrasonic weld |
| METAL WELDING | Pure nickel tabs w/ spot welder |
| CLIP | N/A |
| WARRANTY | 12 months |
| PRODUCT PHOTO |  |