

<b>LMR BATTERY SPECIFICATIONS</b>	PART NUMBER
	<b>BPUKNB57</b>

COMPATIBLE RADIOS	Kenwood NX220, NX320, NX420, NX3200, NX3220, NX3300, NX3320, NX3400, NX3420, TK2140, TK2160, TK2170, TK2360, TK3140, TK3160, TK3170, TK3173, TK3360
REPLACES OEM BATTERY	KNB-57L
COMPATIBLE CHARGERS	Endura EC1-KW3, EC1M-KW3, EC2M-KW3A-D, EC6M-KW3, EC12M-KW3A-D / EVC-KW3 / Kenwood KSC-25LSK, KSC-25SK, KSC-256K
USB CHARGING	Internal circuitry allows charging with 24" USB cable included / status LED indicates charging, charge complete, or fault
VOLTAGE	7.4V
CAPACITY	2000 mAh / 14.8 Wh
CHEMISTRY	Li-Ion
CELL TYPE	Panasonic UR18650ZM2 or equivalent
OPERATING TEMPERATURE	-20° C to +60° C (discharge) / 0° C to +40° C (charge)
CHARGE CYCLES	>300
CHARGE TYPE	Rapid
CONDITIONER COMPATIBLE	Yes (not required for cycle life or battery performance)
PROTECTION TYPES	Short circuit / over-charge / over-discharge / over-temperature monitoring via external charge contact
HOUSING MATERIAL / SEAL	ABS / ultrasonic weld
METAL WELDING	Pure nickel tabs w/ spot welder
CLIP	N/A
WARRANTY	12 months
PRODUCT PHOTO	 <div style="border: 1px dashed black; padding: 5px; display: inline-block; margin-left: 20px;"> <b>Housing Thickness</b>        0.89" / 22.6 mm     </div>