



| | |
|-----------------------------------|------------------|
| LMR BATTERY SPECIFICATIONS | PART NUMBER |
| | BP36229MH |

| | |
|------------------------|--|
| COMPATIBLE RADIOS | Vertex Standard VX500, VX510, VX520, VX520UD, VX530, VX537 |
| REPLACES OEM BATTERY | FNB-29A |
| COMPATIBLE CHARGERS | Endura TWC1-VX5, TWC1M-VX5, TWC6M-VX5 |
| VOLTAGE | 7.2V |
| CAPACITY | 2000 mAh |
| CHEMISTRY | NiMH |
| CELL TYPE | FDK, Panasonic, or equivalent |
| OPERATING TEMPERATURE | -10° C to +65° C (discharge) / 0° C to +40° C (charge) |
| CHARGE CYCLES | 500 |
| CHARGE TYPE | Rapid or trickle |
| CONDITIONER COMPATIBLE | Yes |
| THERMAL PROTECTION | Yes |
| HOUSING MATERIAL | ABS |
| HOUSING SEAL | Ultrasonic weld |
| METAL WELDING | Pure nickel tabs w/ spot welder |
| CLIP | N/A |
| WARRANTY | 12 months |
| PRODUCT PHOTO | |