



LMR BATTERY SPECIFICATIONS	PART NUMBER
	BP5631-1

COMPATIBLE RADIOS	Kenwood NX-210, NX-410, NX-411, TK-2180, TK-3180, TK-5210, TK-5210G, TK-5310, TK-5310G, TK-5410
REPLACES OEM BATTERY	KNB-31A
COMPATIBLE CHARGERS	Endura TWC1-KW4, TWC1M-KW4, TWC2M-KW4-D, TWC6M-KW4, TWC12M-KW-D
VOLTAGE	7.2V
CAPACITY	1400 mAh
CHEMISTRY	NiCd
CELL TYPE	GP or equivalent
OPERATING TEMPERATURE	-10° C to +65° C (discharge) / 0° C to +40° C (charge)
CHARGE CYCLES	500
CHARGE TYPE	Rapid or trickle
CONDITIONER COMPATIBLE	Yes
THERMAL PROTECTION	Yes
HOUSING MATERIAL	ABS
HOUSING SEAL	Ultrasonic weld
METAL WELDING	Pure nickel tabs w/ spot welder
CLIP	N/A
WARRANTY	12 months
PRODUCT PHOTO	