

| | |
|-----------------------------------|-----------------|
| LMR BATTERY SPECIFICATIONS | PART NUMBER |
| | BPBH1301 |

| | |
|--------------------------|--|
| COMPATIBLE RADIOS | HYT TC-500, TC-500U, TC-500V, Blackbox UHF / VHF |
| REPLACES OEM BATTERY | BH1301, BLACKBOX-HCB |
| COMPATIBLE CHARGER / POD | Endura TWC1-HY1 / TWP-HY1 |
| VOLTAGE | 6.0V |
| CAPACITY | 1300 mAh |
| CHEMISTRY | NiMH |
| CELL TYPE | GP or equivalent |
| OPERATING TEMPERATURE | -10° C to +65° C (discharge) / 0° C to +40° C (charge) |
| CHARGE CYCLES | 500 |
| CHARGE TYPE | Rapid or trickle |
| CONDITIONER COMPATIBLE | Yes |
| THERMAL PROTECTION | Yes |
| HOUSING MATERIAL | ABS |
| HOUSING SEAL | Ultrasonic weld |
| METAL WELDING | Pure nickel tabs w/ spot welder |
| CLIP | Included |
| WARRANTY | 12 months |
| PRODUCT PHOTO |  |