



LMR BATTERY SPECIFICATIONS	PART NUMBER
	BPKNB69LI

COMPATIBLE RADIOS	Kenwood TK-2200, TK-2200L, TK-2200LP, TK-2207, TK-2212L, TK-2302VK, TK-2307, TK-2312, TK-2400VP, TK-2402VK, TK-3200, TK-3200L, TK-3200LP, TK-3207, TK-3212L, TK-3300UP, TK-3302UK, TK-3307, TK-3313, TK-3400UP, TK-3402UK
REPLACES OEM BATTERY	KNB-69L
COMPATIBLE CHARGER / POD	Endura TWC1-KW6, TWC1M-KW6, TWC2M-KW6-D, TWC6M-KW6, TWC12M-KW6-D
VOLTAGE	7.4V
CAPACITY	2550 mAh
CHEMISTRY	Li-Ion
CELL TYPE	Sanyo, Panasonic, or equivalent
OPERATING TEMPERATURE	-20° C to +60° C (discharge) / 0° C to +40° C (charge)
CHARGE CYCLES	300
CHARGE TYPE	Rapid
CONDITIONER COMPATIBLE	Yes
THERMAL PROTECTION	Yes
HOUSING MATERIAL	ABS
HOUSING SEAL	Ultrasonic weld
METAL WELDING	Pure nickel tabs w/ spot welder
CLIP	N/A
WARRANTY	12 months
PRODUCT PHOTO	